



Diesel Generator For Home, 10 KW, Electric Start, Fuel Tank 25L , Digital Panel, RemoteController

Brand: Kc Power

SKU: KC10.0-DO

Warranty:

- Rated output of 10 kW with 11 kW maximum power for reliable electricity supply
- Durable single-cylinder diesel engine designed for stable continuous operation
- Digital 5-in-1 control panel with ATS connector and dual sockets for convenient power distribution
- Electric start system with remote controller for simple and efficient generator operation
- Copper-wound alternator with AVR regulation for consistent voltage output

Specifications

Frequency	60 Hz
Rated Voltage	220-240 V
Rated Power	10 kW
Max Output	11 kW
Phase	Single Phase
Power Factor	1
Fuel Tank Capacity	25 L
Fuel Consumption	4.2 L/h
Operating Hours at 100% Load	6 hr
Noise Level at 7 m	≤82 dB(A)
Engine Model	LA188F
Engine Speed	3600 rpm
Starting System	Electric Start
Battery Capacity	30 AH
Engine Type	1 cylinder, 4 stroke, air cooled, vertical, inline, direct injection diesel engine
Displacement	954 cc
Bore x Stroke	90 x 75 mm

Recommended Lubricating Oil	10W-30 or 15W-40
Oil Capacity	3 L
Recommended Fuel	Diesel #0 (Summer), #10 (Winter)
Alternator	Copper winding with AVR
Control Panel	2 sockets, ATS connector, digital panel (5-in-1), remote controller
Dimensions (L x W x H)	910 x 578 x 800 mm
Weight	200 KG
Weight	200 KG